

Reinstalling a Probe that the Linksys Software Does Not Connect to

1. Go to my Bluetooth Places on the Desktop, right click on the OptoWave device and select remove.
2. Right click on the Bluetooth icon in the sys tray. (Make sure the adapter is plugged in, the center is white, and the probe is turned on.)
3. Select Quick Connect/Bluetooth Serial Port/Other Devices (Find Devices)
4. When the Services Dialog Box appears select the Refresh button (If the OptoWave Device is listed in the box do not select it yet.)
5. When the Refresh is complete select the OptoWave device from the list.
6. The software will open a Connecting dialog box. (If you get an error here or on the next step go back to step 3 and repeat.)
7. The software should then ask for the PIN code. Enter the code – 1234.
8. The operating system will then assign a COM port. This should be the same as it was before but be sure to make a note of the COM port it reports in the dialog box.

That should correct the problem. If it does not I would suggest uninstalling the Linksys software and then reinstalling it. I have instructions available for that if you need them.